



## Technical Service Bulletin

**MODEL(S) AFFECTED:** **S5, S9** Walk-Behind Sweepers  
S5 models manufactured before serial number S5004614 (October 2015)  
S9 models manufactured before serial number S9003756 (October 2015)

**SUBJECT:** Static shock nuisance at control handle while operating. Static path is not sufficient to dissipate voltage potential.

**PURPOSE:** To eliminate static shock nuisance, reposition the anti-static chain as described below.  
For the S5 model, the Ground Wire Static Kit p/n 9014771 is also required.

**NOTES:** **Warranty Information:** Standard warranty terms apply.

### Procedure:

Tool Required: 5mm hex wrench

**FOR SAFETY: Before servicing machine, park machine on level surface and remove key.**

1. Carefully tilt machine back on handle.
2. Remove the anti-static chain, screw and washer from left side of machine as shown.



3. Re-install chain, screw and washer on the right side of machine as shown. Re-install shorter screw from right side on the left side.



4. **S5 Model Only:** Install Ground Wire Static Kit.

### S5 - Ground Wire Static Kit Installation:

#### S5 Kit 9014771 Contents

**Part Description**  
9 in/23cm, 17GA/  
1.0mm<sup>2</sup> wire with M5  
and M6 ring terminals



Tools Required: 4mm and 5mm hex wrench

**FOR SAFETY: Before servicing machine, park machine on level surface and remove key.**

1. Carefully tilt machine back on handle.
2. Remove side brush from machine.
3. Remove the two hex screws as shown.



4. Route kit wire as shown and secure with the removed screws.

